Z Series Specialty Components TDQ-150





Parasound's digital quartz radio tuner, the TDQ-150, may just be the highest quality mini-tuner in the world. Outstanding sound and convenient features such as remote, DC triggering, IR control input, and 30 station presets have made it a favorite for desktop, dorm and distributed audio systems. It can be controlled by our Z-pre remote as well, relieving gizmo clutter. Want minimum footprint with maximum radio? Here it is!

What is Parasound's Z-Series? It's the highest-fidelity set of matched miniatures available today. Only 2" tall and 9-1/2" wide, Z's can stand alone on the smallest surface, or rack mount side by side. Wherever you want a minimum-size system with maximum-quality sound — on desktop, counter, in-wall or multi-zone — the Z-Series is your compact sonic solution.

Specifications

Shipping weight: 7 lbs

Tuning range: FM 87.5 MHz to 108 MHz; AM 520 kHz to 1610 kHz FM sensitivity: Mono - IHF 10.8 dBf Stereo - IHF 37.2 dBf for 50 dB of quieting AM sensitivity: IHF 10 μV/m S/N ratio: > 74 dB stereo; 65 dB IHF weighted FM stereo separation: 50 dB @ 1 kHz; 40 dB @ 10 kHz Selectivity: FM - 80 dB; AM - 30 dB FM frequency response: 30 Hz - 15 kHz +/- 1 dB AM frequency response: 20 Hz - 4.5 kHz +/- I dB Total harmonic distortion: FM Mono <0.08%; FM Stereo < 0.2% AM < 0.5% Capture ratio: < 1.5 dB AM suppression: 60 dB Power requirements: I 10 V - I 20 V, 8 W Dimensions: 9-1/2" w x 2" h x 7" d, 1-3/4" h without feet

Features

Automatic, manual, and preset tuning
Thirty station presets with long-term memory
Ultra wide-band IF section for low distortion
CMOS solid state switching
Regulated power supply
Audiophile-grade components
AC line and DC triggering capability
Fully remote controlled with discrete on/off commands
Rear panel infrared remote input
9-1/2" wide front panel; I rack space high
Fastening hardware available for rack mounting
Parasound's 10 years parts, 5 years labor warranty



PARASOUND