

Audiophile Tuner
TDQ-1600

Parasound's **TDQ-1600** tuner has enough sensitivity and selectivity to lock in all your favorite stations, and enough audio quality to ensure that you enjoy them. Using either the front panel controls or your remote you can auto scan the dial, manually pick your frequency or select from 20 user preset stations. It is even capable of control from another room with an infrared remote input connection on the back panel. All components are audiophile grade and designed to bring your favorite FM/AM stations into your home with clarity. This full-chassis tuner completes any home audio system.



Features

- Automatic, manual, and preset tuning
- Ultra Wideband IF section for low distortion
- CMOS solid state switching
- Regulated power supply
- Audiophile-grade components
- Twenty station presets with long-term memory
- Fully remote controlled
- Silver-plated OFC internal wiring
- Rear panel infrared remote input
- Heavy-duty chassis
- 2 rack space high front panel
- Fastening hardware available for rack mounting
- Parasound's 10 years parts, 5 years labor warranty

Specifications

- Tuning range: FM 87.5 MHz to 108 MHz; AM 520 kHz to 1610 kHz
- FM sensitivity: Mono - IHF 10.8 dBf
Stereo - IHF 37.2 dBf for 50 dB of quieting
- AM sensitivity: IHF 350 μ V/m
- FM stereo separation: 50 dB @ 1 kHz; 40 dB @ 10 kHz
- Selectivity: FM 80dB; AM 50dB
- FM frequency response: 20 Hz - 15 kHz +/- 1 dB
- AM frequency response: 20 Hz - 4.5 kHz +/- 2 dB
- Total harmonic distortion: FM Mono < 0.08%; FM Stereo < 0.2%
AM < 0.6%
- Capture ratio: 1 dB
- AM Suppression: 60 dB
- Dimensions: 17-1/4" w x 4-1/8" h x 12-3/8" d, 3-1/2" h without feet
- Shipping weight: 20 lbs.



PARASOUND

*Parasound Products, Inc. 950 Battery Street, San Francisco, CA 94111
415-397-7100 / FAX 415-397-0144 www.parasound.com*