It's easy to upgrade your 5.1 system to the latest standards with this new Z-series miniature, the CSE 6.1 center/surround expander. Just insert it between your preamp's rear-channel outputs and your amp, and voila: a rear center (two if you prefer), a rear subwoofer channel, and even two rear ceiling or in-wall speaker channels – everything needed to buff your system up to 9.2 – all become available instantly. Compatible with Dolby Surround EX, THX EX, and DTS ES matrix surround formats, the CSE can provide that extra circular-surround wallop that makes for total sonic immersion!

What is Parasound's Z-Series? It's the highest-fidelity set of matched miniatures available today. Only 2" tall and 9-1/2" wide, Z's can stand alone on the smallest surface, or rack mount side by side. Wherever you want a minimum-size system with maximum-quality sound – on desktop, counter, in-wall or multi-zone – the Z-Series is your compact sonic solution.

Features

Works with any 5.1 surround processor and most receivers

Utilizes SRS Circle Surround matrix processing

6.1 information present indicator

Fully remote controllable

2 rear center pre outputs

Special output jacks for overhead or side ambient effects

Rear subwoofer output jack

Adjustable rear subwoofer low-pass filter

LS, RS Unity gain setting makes level setting easy

Gold plated RCA jacks

External 12 V power supply

Rear panel infrared remote input

9-1/2" wide front panel; 1 rack space high

Fastening hardware available for rack mounting

Parasound's 10 years parts, 5 years labor warranty

Specifications

Frequency response: 10 Hz to 150 kHz LS, RS
    100 Hz to 150 kHz CS; 10 Hz to 120 Hz Subwoofer

Harmonic distortion: < 0.05 % 1 kHz

IM distortion: < 0.06%

Input impedance: 47 kΩ

Output impedance: 600 Ω

S/N ratio: > 70 dB

Dynamic range: > 85 dB

Crosstalk: > 50 dB

Power Supply: 110 V - 120 V, 60 Hz AC Input
    15 V AC - 400 mA Output

Dimensions: 9-1/2" w x 2" h x 7" d, 1-3/4" h without feet

Shipping weight: 7 lbs.